

Technical Support

For Cisco Unity Connection support, contact 33200, 732743200, or send an email to Isthelp@umdj.edu.



Cisco, Cisco Unity, Cisco Systems, and the Cisco Systems logo are registered trademarks or trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries. All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0705R) Copyright © 2012 Cisco System, Inc. All rights reserved.

For Optional Conversation 1, Cisco Unity Connection

April 12, 2012 14:32:24



Connection Phone Menus and Shortcuts

Quick Reference Guide

This card lists the most frequently used Cisco Unity Connection menus and shortcut keys for managing messages and user settings by phone.

Accessing Connection

1. Call Cisco Unity Connection.

From your desk phone:

- Dial 23400

Or

- Press the Messages button on your phone.

From outside your organization:

- Dial 973-972-3400

2. If you are calling from another phone within your organization or from outside the organization, press * when Cisco Unity Connection answers.
3. If prompted, enter your Connection ID (your 5 digit desk phone extension), and press #.
4. Enter your password, and press #.

Main Menu and Shortcuts

Key(s) **Action**

Key(s)	Action
1	Play new messages
2	Send a message
3	Review old messages
4	Change setup options
41	Change greetings
412	Turn on/off alternate greeting
421	Change message notification
423	Choose full or brief menus
44	Change transfer settings
5	Find messages
51	Find messages from a user
52	Find messages from all outside callers
53	Find messages from a specific outside caller

During Message Menu

While listening to a message, press:

Key(s) **Action**

Key(s)	Action
1	Rewind
11	Repeat message
2	Pause/Resume
3	Fast-forward
4	Slow playback
6	Fast playback
#	Skip message, save as is

After Message Menu

After listening to a message, press:

Key(s) **Action**

Key(s)	Action
1	Rewind
4	Repeat message
5	Play message properties
6	Forward message
7	Delete
8	Reply
82	Reply to all
88	Call the sender
9	Save
#	Save as is
##	Save as new

Entering Recipients

To change entry mode, press:

Key(s) **Action**

##	Switch between addressing a message by name and addressing by extension
-----------	---

Selecting Recipients

To select recipients from a list, press:

Key(s) **Action**

0	Help
1	Repeat name
7	Previous name
77	First name in list
9	Next name
99	Last name in list
#	Select name
*	Exit list

Send Message Menu

After addressing and recording, press:

Key(s) **Action**

1	Mark urgent
2	Request return receipt
3	Mark private
4	Request future delivery
5	Review recording
6	Rerecord
7	Add to recording
91	Add a recipient
92	Play all recipients (and delete recipients)
*	Cancel message
#	Send message